

CED

Mounting & Wiring

Installation Instructions

Chain, pendant or surface mounting · 120–277 VAC

A) MOUNTING METHODS

CHAIN MOUNT (STANDARD)

Hang the luminaire from the structure on the supplied V-hooks and 1 m chain ($\frac{1}{8}$ "), one chain set per fixture, with the fixture level and the supply cord or conduit supported independently of the chain.

PENDANT MOUNT (KIT)

Fit the pendant mount kit and attach the luminaire to $\frac{1}{2}$ " rigid conduit from the J-box above; keep the conduit plumb and the fixture level.

SURFACE MOUNT (KIT)

Fit the surface mount kit and fasten the luminaire to the solid surface with anchors rated for the fixture weight (7.7 to 10.0 lb) plus the kit.

OPTICS

Rotate the optical panels, up to 150 degrees, to put the light where the space needs it; fit the wire guard kit for the size where ordered.

B) WIRING & SYSTEM TEST

1. Turn off the branch circuit before installation. All wiring per NEC and local code.
2. Connect the 120–277 VAC supply to the driver leads; connect the 0–10 VDC dimming leads to the control where dimming is used, observing polarity.
3. Sage Relay option: the relay is factory installed in the luminaire; connect it to the Sage central battery low voltage run per the Sage Relay installation guide.
4. Energize and verify output and dimming; where the Sage Relay is fitted, verify emergency operation per the Sage Relay installation guide. The luminaire operates from -40 to 50 °C ambient.
5. Inspection: check the chain, hooks or kit fasteners and the lenses as local practice requires.

SAVE THESE INSTRUCTIONS

"Engineered for the spaces it protects."