

TYPE _____ · DATE _____ · PROJECT _____

<p>CB COMPATIBLE Powers from central battery</p>	<p>ADJUSTABLE OUTPUT Factory set for any fixture</p>	<p>DIMMING COMPATIBLE Works with all controls</p>	<p>UL LISTED UL 924 compliant</p>
---	---	--	--

SR1

SR1

GENERAL DESCRIPTION

Emergency Lighting Control converting LED luminaires to central battery emergency operation. Factory adjustable output optimizes illumination for any fixture. Ideal for compact downlights and space-constrained luminaires in normal power range 10W to 70W..

CONSTRUCTION & OPERATION

Factory or field installable in fixture Fire and Electrical Enclosure.

Compatible with all dimming and lighting controls.


Input 24 VDC with constant emergency output adjustable from 5W to 22W.

Output voltage sensing to 41V.

Available for fixtures from 10W to 70W normal power.

High efficiency 90% at 24VDC.

UL Listed per UL Standard 924.



SPECIFICATIONS			
Input	24 VDC		
Emergency Output	5W to 22W (adjustable)		
Output Voltage	Up to 41V (auto sensing)		
Normal Fixture Load	10W to 70W+		
Efficiency	90% @ 24VDC		
Listings	UL 924 / CSA C22.2 No. 141		
<table border="0"> <tr> <td style="border: 1px solid black; padding: 5px;">CB COMPATIBLE</td> <td style="border: 1px solid black; padding: 5px;">SAGE LIVE™ READY</td> </tr> </table>		CB COMPATIBLE	SAGE LIVE™ READY
CB COMPATIBLE	SAGE LIVE™ READY		

ORDERING INFORMATION

Series	Watts	Volts	CODE	OPTION / DESCRIPTION
SR1	X Watts		V3	5-22V

Ordering Example: SR1-10-V3

<p>CONFORMS TO</p> <p>UL 924 / CSA C22.2 #141</p>	<p>ASSEMBLED IN USA</p> <p>Per Buy American Act</p>
---	---

“Engineered for the spaces it protects.”