

TYPE \_\_\_\_\_ · DATE \_\_\_\_\_ · PROJECT \_\_\_\_\_

 <b>CB COMPATIBLE</b> Powers from central battery	 <b>HIGH BAY RATED</b> Up to 100W+ normal load	 <b>HIGH VOLTAGE</b> Driver output sensing to 100V	 <b>ADJUSTABLE OUTPUT</b> Optimized per fixture
---	--	--	---

# SR3

SR3

## GENERAL DESCRIPTION

Emergency Lighting Control for high-bay luminaires with normal power 30W to 100W or higher. Supports AC LED drivers with output up to 100V. Factory adjustable emergency output 5W to 20W with hi-temp VHB tape and flange screw mount..

## CONSTRUCTION & OPERATION

- Factory or field installable in fixture enclosure.
- VHB tape and screw flange mount standard.
- Input 24 VDC with adjustable emergency output 5W to 20W.
- Voltage sensing range 30V to 100V for high-voltage AC driver compatibility.
- For high-bay fixtures 30W to 100W+ normal power.
- UL Listed per UL Standard 924.



SPECIFICATIONS	
<b>Input</b>	24 VDC
<b>Emergency Output</b>	5W to 20W (adjustable)
<b>Output Voltage</b>	30V to 100V (auto sensing)
<b>Normal Fixture Load</b>	30W to 100W+
<b>Mount</b>	VHB tape + screw flange
<b>Listings</b>	UL 924
<div style="display: flex; justify-content: space-around;"> <span>CB COMPATIBLE</span> <span>SAGE LIVE™ READY</span> </div>	

## ORDERING INFORMATION

Series	Watts	Volts	CODE	OPTION / DESCRIPTION
SR3	X Watts		V1	27-54V
			V2	5-41V
			V3	5-22V

Ordering Example: SR3-50-V1

<b>CONFORMS TO</b>  UL 924 / CSA C22.2 #141	<b>ASSEMBLED IN USA</b>  Per Buy American Act
---	---

*“Engineered for the spaces it protects.”*