

JUN

Mounting & Wiring

Installation Instructions

Surface, chain or cable mounting · 120–277 VAC

A) MOUNTING METHODS

SURFACE MOUNT (STANDARD KIT)

Fasten the surface mount kit to the ceiling or structure with anchors rated for the fixture weight (4.64 lb) and clip the luminaire to it; keep the latches closed and the lens seated for the vapor tight seal.

CHAIN OR CABLE SUSPENSION

Hang the luminaire on the supplied V-hooks with chain (sold separately) or on the optional 3 m or 5 m cable mount kit, level, with the supply supported independently.

SENSOR

Screw the sensor (ordered separately) into the sensor-ready receptacle and program it with the remote control; cord and plug sets do not affect sensor installation.

B) WIRING & SYSTEM TEST

1. Turn off the branch circuit before installation. All wiring per NEC and local code.
2. Connect the 120–277 VAC supply to the driver leads; connect the 0–10 VDC dimming leads to the control where dimming is used, observing polarity.
3. Sage Relay option: the relay is factory installed in the luminaire; connect it to the Sage central battery low voltage run per the Sage Relay installation guide.
4. Energize and verify output and dimming; where the Sage Relay is fitted, verify emergency operation per the Sage Relay installation guide.
5. Inspection: check the latches, the lens seal and the mounting as local practice requires.

SAVE THESE INSTRUCTIONS

“Engineered for the spaces it protects.”