

· TYPE _____ · DATE _____ · PROJECT _____

DUAL-FUNCTION
Normal or emergency from one fixture

LOW PROFILE
Recessed, mounts from 4 ft up

POWERFUL
High output where it's needed

SAGE LIVE™
Monitored on the central battery

Radiant

RAD

GENERAL DESCRIPTION

A low-profile, powerful LED recessed fixture that runs in either normal or emergency mode — mountable as low as 4 ft from the floor. Part of the Sage central battery system, monitored through Sage Live.

CONSTRUCTION & OPERATION

Operates with Sage central battery including low voltage normal lighting operation. (See Sage central battery data sheet)

Dual function operation for Night or Security lighting as well as emergency lighting.

Over 50,000 hour lamp life in normal use.

Remote power supply for BB models.



SPECIFICATIONS

Operation	BB · AC · RE
LED Life	50,000 hours
Operating Temp	BB 0–50 · AC/RE -40–50 °C
Warranty	10 year warranty

Listed to UL 924, NFPA 101; cETLus (Intertek); BABA; BAA; WET

SELF-DIAGNOSTIC

UL 924 LISTED

ORDERING INFORMATION

Series	Operation	Power	Face Plate
RAD	BB – Battery Backup	10 – 10 watts emergency and normal power	W – Satin White
	AC – AC Supply (120/277V)		K – Black
	RE – Remote with Central Battery		A – Aluminum
			B – Dark Bronze
			X – Custom

Ordering Example: RAD-RE-10-W-LV

Options: LV Louvered Face · DAC Dual AC input (AC models) · CW1 3800K · CW2 3200K · CW3 2900K

LISTED TO



ASSEMBLED IN USA



“Engineered for the spaces it protects.”