

TYPE _____ · DATE _____ · PROJECT _____

 CB COMPATIBLE Powers from central battery	 PANEL FIXTURE For 2x2 and 2x4 lay-in designs	 ADJUSTABLE OUTPUT Optimized per fixture	 EASY INSTALL VHB tape or screw mount
---	--	---	--

SR2


SR2

GENERAL DESCRIPTION

Emergency Lighting Control designed for 2x2 and 2x4 LED flat panels and lay-in fixtures. Thermoplastic housing with hi-temp VHB tape mount or optional screw flange. Factory adjustable emergency output from 5W to 24W for fixtures 10W to 70W normal power..

CONSTRUCTION & OPERATION

- Factory or field installable in fixture enclosure.
- Compatible with all dimming and lighting controls.
- Hi-temp VHB tape mount standard, optional screw flange.
- Input 24 VDC with adjustable emergency output 5W to 24W.
- Output voltage sensing to 41V.
- For fixtures 10W to 70W normal power.
- UL Listed per UL Standard 924.



SPECIFICATIONS	
Input	24 VDC
Emergency Output	5W to 24W (adjustable)
Output Voltage	Up to 41V (auto sensing)
Normal Fixture Load	10W to 70W+
Mount	VHB tape / optional screw flange
Listings	UL 924

CB COMPATIBLE

SAGE LIVE™ READY

ORDERING INFORMATION

Series	Watts	Volts	CODE	OPTION / DESCRIPTION
SR2	X Watts		V1	27-54V
			V2	5-41V
			V3	5-22V

Ordering Example: SR2-20-V2

CONFORMS TO UL 924 / CSA C22.2 #141	ASSEMBLED IN USA Per Buy American Act
---	---

“Engineered for the spaces it protects.”