

TYPE _____ · DATE _____ · PROJECT _____

 CB COMPATIBLE Powers from central battery	 DIE-CAST HOUSING Rugged aluminum enclosure	 J-BOX MOUNT External junction box cover mount	 ADJUSTABLE OUTPUT Factory set per fixture
---	--	---	---

SR6

SR6

GENERAL DESCRIPTION

Emergency Lighting Control in rugged die-cast aluminum enclosure for external junction box cover mount. Designed for downlights and flat panel LED fixtures 10W to 70W normal power. Factory adjustable emergency output 5W to 24W.

UL Listed per UL 924.

CONSTRUCTION & OPERATION

Die-cast aluminum enclosure mounts on junction box cover.

Factory or field installable.

Compatible with all dimming and lighting controls.

Input 24 VDC with adjustable emergency output 5W to 24W.

Output sensing to 41V.

For fixtures 5W to 70W normal power.

UL Listed per UL 924.



SPECIFICATIONS	
Input	24 VDC
Emergency Output	5W to 24W (adjustable)
Output Voltage	Up to 41V (auto sensing)
Normal Fixture Load	5W to 70W+
Enclosure	Die-cast aluminum
Listings	UL 924 / CSA C22.2 No. 141-15
<div style="display: flex; justify-content: space-around;"> CB COMPATIBLE SAGE LIVE™ READY </div>	

ORDERING INFORMATION

Series	Watts	Volts	CODE	OPTION / DESCRIPTION
SR6	X Watts		V1	27-54V
			V2	5-41V
			V3	5-22V

Ordering Example: SR6-20-V2

CONFORMS TO UL 924 / CSA C22.2 #141	ASSEMBLED IN USA Per Buy American Act
---	---

“Engineered for the spaces it protects.”